

In order to meet the FCC policies, the frequency ranges of the TYT TH-9800 radios sold by Radioddity are locked in 28-29.7Mhz, 50-54Mhz, 144-148MHz and 420-450MHz. But you can unlock the frequency range if needed.

How the unlock the frequency ranges?

1. Connect your TH-9800 with the programming software and load ("read") it to the software

2. Press "Ctrl+F11" and enter the password "9800TYT";

3. Edit the frequency range:

Maximum Frequency Range:

- 26-33MHz (RX/TX) (AM band RX)

- 47-54MHz (RX/TX) (AM band RX)

- 136-174MHz (RX/TX)

- 400-480MHz (RX/TX)

4. Write to the radio, turn off the radio and then turn it back on. Now, it can work in the expected frequency range.

If you need any further assistance or have any question, please feel free to contact us via <support@radioddity.com>. Hope you enjoy your new radio!